


Cabinet Impedance .....	8 $\Omega$
Individual Speaker impedance .....	8 $\Omega$ (10")
.....	8 $\Omega$ (5")
Capacitor .....	2.2 $\mu$ F
Wiring configuration .....	Series/Parallel
Port Type .....	Tuned, Vent-Port
Frequency Response .....	30Hz to 12kHz
Power Handling .....	400 watts
SPL .....	99dB@1W/1m
Magnet .....	60 oz and 16 oz
Voice Coil .....	1.5" (10")
.....	1" (5")
Inputs .....	(2) Parallel, 1/4"
Dimensions .....	26.5"(H) X 24"(W) X 18"(D)
Weight .....	99lb
Driver SKU .....	3-10XL8 (10")
Driver SKU .....	3-5XL8 (5")

Looking into cabinet as if from rear view



All Speakers are Positive on right and Negative on left when facing speaker rear with terminals at bottom.